



Length	Nestbox Height
12'	14'
14'	16'
16'	18'

Pivot & Latch Detail

Attach Pivot Brace to Pole Brace with (5) wood screws. Attach Main Pole to Pole Brace with (10) wood screws. (Locate Pole Brace 24" from bottom of Main Pole and Pivot Brace)

Lowered Position
Remove Latch Bolt and rotate Tower to horizontal position

Pole Assembly

Pole Assembly

Quan	Component	Material / Size
1	Main Pole	2 x 4 x 12', 14' or 16' - see chart
1	Pole Brace	2 x 4 x 8'
1	Pivot Brace	2 x 4 x 4'
1	Ground Post	4 x 4 x 6' - treated
1	Pivot Bolt	1/2" x 8" Galvanized hex head bolt
1	Latch Bolt	1/2" x 8" Galvanized concrete anchor bolt
1	Lock Nut	1/2" - for Pivot Bolt
1	Nut	1/2" - for Latch Bolt
3	Washers	1/2"
15	Wood screws	#8 x 3" Exterior (deck) screws

Nestbox Mounting Tower
Designed by: Tom Comfort